



Generators



Dependable jobsite power

www.multiquip.com



Portable Generators



Meet MultiQuip's newest generator models... the preferred generators of contractors everywhere!

- **Control Panel** — Rugged new look withstands the rough handling on the job site or in the back of a truck.
- **Receptacles** — Additional twist-lock receptacles have been added for operator convenience.
- **Lifting Bail** — Standard on 3.6 kW to 6 kW models. Hinged design lays flat when not in use.
- **Engines** — MultiQuip generators are available with Honda GX-Series industrial grade engines.
- **Electric Start** — available on 6 kW models; standard on 9.7 kW model.
- **Brushless design** — low maintenance for years of dependable service.
- **Superior voltage regulation** — helps to keep tools and equipment running at optimal levels; helps them last longer.
- **Full-panel GFCI protection** that is OSHA and NEC compliant.

Voltmeter

This feature serves as a convenient diagnostic tool on the jobsite. The operator can quickly tell whether or not the generator is producing the correct voltage and prevent overheating of expensive tools and equipment.



Silent Type Muffler

Reduces noise level on Honda units. USFS-approved spark arrestors standard on 2.5kW through 6kW Honda-powered models.

Reliability

GA-Series generators use a brushless design that minimizes maintenance by eliminating the carbon brushes and slip rings common on competitive models.

The best warranty in the industry.

All GA-Series generators are covered by a two-year parts and labor warranty.

There's a size and model for every application...



2500 watts max.
Honda engine
Recoil start
GA25H



3600 watts max.
Honda engine
Recoil start
GA36HB



9700 watts max.
Honda engine
Recoil/Electric start
GA6HEAB



9700 watts max.
Honda engine
Recoil/Electric start
GA97HA



UWK Wheel Kit
For 2.5kw through 6kw models;
Shown with handles in both up and
down positions.



Unit shown on
optional WKT97
Wheel Kit

Portable Generator Specifications

MODEL	GA25H	GA36HAB	GA6HAB	GA6HEAB	GA97HEB
Alternator Design	Brushless				
Maximum Watts	2,500	3,600	6,000	6,000	9,700
Continuous Watts	2,200	3,200	5,000	5,000	8,400
Voltage	120V	120/240V			
Max. Amp @ 120V	20.8	30	50	50	80.8
Cont. Amp @ 120V	18.3	26.6	41.6	41.6	70
Max. Amp @ 240V	N/A	15	25	25	40.4
Cont. Amp @ 240V	N/A	13.3	20.8	20.8	35
Frequency/Phase	60 Hz / Single phase				
Voltmeter	Standard				
Full Power Switch	N/A	Standard			N/A
RECEPTACLES* AND CIRCUIT BREAKERS					
5-20R 125V GFCI 20A	✓	✓ (2)	✓ (2)	✓ (2)	✓ (2)
L5-20R 125V; T-Lock 20A	✓	✓	✓	✓	
L5-30R 125V; T-Lock 30A		✓	✓	✓	✓
L6-20R 250V; T-Lock 20A					✓
L14-20R 125/250V; T-Lock 20A		✓			
L14-30R 125/250V; T-Lock 30A			✓	✓	✓
CS-6369; 125/250VAC 50A					
ENGINE					
Engine Manufacturer	Honda	Honda	Honda	Honda	Honda
Engine Model	GX-160	GX-240	GX-340	GX-340	GX-630
Horsepower (KW)††	4.8 (4.1)	7.1 (5.3)	9.5 (7.1)	9.5 (7.1)	20.8 (15.5)
Rated Speed — RPM	3,600				
Low Oil Shutdown	Standard				
Starting Systems**	Recoil			Recoil with Electric	Electric
Fuel Capacity — gal (ltr)	3.2 (12)	5.0 (19)	5.0 (19)	5.0 (19)	10.0 (37.8)
Running Time — hr./tank***	8.9	9.0	5.7	5.7	8
Fuel Gauge	Standard				
Automatic Idle Control	N/A	Standard			
Sound Level dB@ 23 ft.	74	76	79	79	79
DIMENSIONS AND WEIGHT					
Length — in. (cm)	21 (53)	24½ (62)	25½ (65)	25½ (65)	31½ (80)
Width — in. (cm)	17¾ (45)	22 (56)	22 (56)	22½ (57)	21¼ (54)
Height — in. (cm)	20 (51)	21¼ (54)	21¼ (54)	21¼ (54)	27½ (70)
Dry Weight — lbs. (kg)	110 (50)	170 (77)	194 (88)	216 (98)	342 (155)
OPTIONS					
Wheel Kit	UWKB				WKT-97
Trailer	N/A				

© COPYRIGHT 2012, MULTIQUIP INC.

†† Engine power ratings are calculated by the individual engine manufacturer and the rating method may vary among engine manufacturers. Multiquip Inc. and its subsidiary companies makes no claim, representation or warranty as to the power rating of the engine on this equipment and disclaims any responsibility or liability of any kind whatsoever with respect to the accuracy of the engine power rating. Users are advised to consult the engine manufacturer's owners manual and its website for specific information regarding the engine power rating.

All features and specifications are subject to change without notice.
Version (01-12_BD)
Units manufactured by Denyo Mfg. Co.

Connect with us on



* See receptacle chart on Page 7.

** Electric start models are shipped less battery.

*** All running times computed at full load using fuel consumption rates supplied by engine manufacturer.

† Requires adapter kit.

Note: Some units may be shown with optional equipment.



MULTIQUIP INC.
POST OFFICE BOX 6254
CARSON, CA 90749
310-537-3700 • 800-421-1244
FAX: 310-537-3927
E-MAIL: mq@multiquip.com
www.multiquip.com